

*Sub A1*  
A METHOD OF ESTIMATING THE PITCH OF A SPEECH SIGNAL  
USING A BINARY SIGNAL, USE OF THE METHOD, AND A  
DEVICE ADAPTED THEREFOR

*add A2*  
*A2*  
Field of the Invention

The invention relates to a method and device for  
estimating the pitch of a speech signal, for example,  
in telephones.

Background of the Invention

In many speech processing systems it is desirable to  
know the pitch period of the speech. As an example,  
several speech enhancement algorithms are dependent  
on having a correct estimate of the pitch period. One  
field of application where speech processing  
algorithms are widely used is in mobile telephones.

A well known way of estimating the pitch period is to  
use the autocorrelation function, or a similar  
conformity function, on the speech signal. An example  
of such a method is described in the article D.A.  
Krubsack, R. J. Niederjohn, "An Autocorrelation Pitch  
Detector and Voicing Decision with Confidence  
Measures Developed for Noise-Corrupted Speech", IEEE

5 Transactions on Signal Processing, vol. 39, no. 2,  
pp. 319-329, Febr. 1991. The speech signal is  
divided into segments of 51.2 ms, and the standard  
short-time autocorrelation function is calculated for  
each successive speech segment. A peak picking  
algorithm is applied to the autocorrelation function  
of each segment. This algorithm starts by choosing  
the maximum peak (largest value) in the pitch range  
of 50 to 333 Hz. The period corresponding to this  
10 peak is selected as an estimate of the pitch period.

15 However, such a basic pitch estimation algorithm is  
not sufficient. In some cases pitch doubling can  
occur, i.e. the highest peak appears at twice the  
pitch period. The highest peak may also appear at  
another multiple of the true pitch period. In these  
cases a simple selection of the maximum peak will  
provide a wrong estimate of the pitch period.

20 The above-mentioned IEEE article also discloses a  
method of improving the algorithm in these  
situations. The algorithm checks for peaks at one-  
half, one-third, one-fourth, one-fifth, and one-sixth  
of the first estimate of the pitch period. If half of  
25 the first estimate is within the pitch range, the  
maximum value of the autocorrelation within an

interval around this half value is located. If this new peak is greater than one-half of the old peak, the new corresponding value replaces the old estimate, thus providing a new estimate which is presumably corrected for the possibility of the pitch period doubling error. This test is performed again to check for double doubling errors (fourfold errors). If this most recent test fails, a similar test is performed for tripling errors of this new estimate. This test checks for pitch period errors of sixfold. If the original test failed, the original estimate is tested (in a similar manner) for tripling errors and errors of fivefold. The final value is used to calculate the pitch estimate.

However, this known algorithm is rather complex and requires a high number of calculations, and these drawbacks make it less usable in real time environments on small digital signal processors as they are used in mobile telephones and similar devices.

Thus, there is need for a method and a device for estimating pitch of a speech signal especially where small digital signal processors are used, such as in mobile telephones and other devices.

5 It is an object of the invention to provide a method and device of the above-mentioned type which is less complex than the prior art methods, such that the method is suitable for small digital signal processors.

**SUMMARY OF THE INVENTION**

10 The method and device of the invention for estimating the pitch of a speech signal are of the type where the speech signal is divided into segments, a conformity function for the signal is calculated for each segment, and peaks in the conformity function are detected. The invention also relates to the use  
15 of the method in a mobile telephone. Further, the invention relates to a device adapted to estimate the pitch of a speech signal. According to the invention, the inventive method comprises the steps of providing an intermediate signal derived from the  
20 speech signal, converting the intermediate signal to a binary signal, which is set to logical "1" where the intermediate signal exceeds a pre-selected threshold and to logical "0" where the intermediate signal does not exceed the pre-selected threshold,  
25 calculating the autocorrelation of the binary signal, and using the distance between peaks in the auto-

correlation of the binary signal as an estimate of the pitch.

The invention also resides in a device adapted to estimate pitch of a speech signal, comprising:

a sampler for sampling the speech signal to obtain a series of samples,

a divider for dividing the series of samples into segments, each segment having a fixed number of consecutive samples,

an autocorrelation calculation unit for calculating for each segment a conformity function for the signal, and

a peak detector for detecting peaks in the conformity function, the device further comprising a programmed unit:

for providing an intermediate signal derived from the speech signal,

for converting said intermediate signal to a binary signal, said binary signal being set to logical "1" where the intermediate signal exceeds a pre-selected threshold and to logical "0" where the intermediate signal does not exceed the pre-selected threshold,

for calculating the autocorrelation of the binary signal, and

for using the distance between peaks in the autocorrelation of the binary signal as an estimate of the pitch.

5 The calculation of the autocorrelation of the binary  
signal takes only a fraction of the computational  
resources needed for the prior art algorithms. Since  
there are only values in some positions of the binary  
signal, the values of the resulting autocorrelation  
10 will occur around zero and around the pitch period of  
the speech signal, and there will only be a few  
values separated from zero. Thus, the pitch period  
can easily be estimated to the distance between the  
values at position zero and the values separated from  
15 zero. Elaborate processing and operations needed in  
prior art algorithms where a specific value has to be  
found in a vector of numbers is thus avoided.

In one embodiment the intermediate signal may be  
20 provided by filtering the speech signal through a  
filter based on a set of filter parameters estimated  
by means of linear predictive analysis (LPA). In this  
way much of the smearing of the original speech  
signal is removed. Alternatively, the intermediate  
25 signal may be provided by calculating the  
autocorrelation of a signal derived from the speech

signal by filtering the speech signal through a filter based on a set of filter parameters estimated by means of linear predictive analysis (LPA). This solution also removes most of the smearing of the original speech signal, and further the possibility of clearer peaks in the intermediate signal is improved.

If the peak corresponding to the distance between the peaks is represented by a number of samples, the best estimate is achieved when the sample having the maximum amplitude of said conformity function is selected as the estimate of the pitch.

Expediently, in an embodiment, the inventive method is used in a mobile telephone, which is a typical example of a device having only limited computational resources.

As mentioned, the invention further relates to a device adapted to estimate the pitch of a speech signal. The device comprises means for sampling the speech signal to obtain a series of samples, means for dividing the series of samples into segments, each segment having a fixed number of consecutive samples, means for calculating for each segment a

conformity function for the signal, and means for detecting peaks in the conformity function.

5 The device further comprises means for providing an intermediate signal derived from the speech signal, means for converting said intermediate signal to a binary signal, said binary signal being set to logical "1" where the intermediate signal exceeds a pre-selected threshold and to logical "0" where the  
10 intermediate signal does not exceed the pre-selected threshold, means for calculating the autocorrelation of the binary signal, and means for using the distance between peaks in the autocorrelation of the binary signal as an estimate of the pitch; a device  
15 less complex than prior art devices is achieved, which also avoids the pitch halving situation.

In one embodiment the device may be adapted to provide the intermediate signal by filtering the  
20 speech signal through a filter based on a set of filter parameters estimated by means of linear predictive analysis (LPA). In this way much of the smearing of the original speech signal is removed.

25 Alternatively, the device may be adapted to provide the intermediate signal by calculating the



5 autocorrelation of a signal derived from the speech  
signal by filtering the speech signal through a  
filter based on a set of filter parameters estimated  
by means of linear predictive analysis (LPA). This  
solution also removes most of the smearing of the  
original speech signal, and further the possibility  
of clearer peaks in the intermediate signal is im-  
proved.

10 If the peak corresponding to the distance between the  
peaks is represented by a number of samples, the best  
estimate is achieved when the device is adapted to  
select the sample having the maximum amplitude of  
said conformity function as the estimate of the  
15 pitch.

In an expedient embodiment of the invention, the  
device is a mobile telephone, which is a typical  
example of a device having only limited computational  
20 resources.

In another embodiment the device is an integrated  
circuit which can be used in different types of  
equipment.  
25

**BRIEF DESCRIPTION OF THE DRAWING**

The invention will now be described more fully below  
with reference to the drawing, in which

5

figure 1 shows a block diagram of a pitch detector  
according to an embodiment of the invention,

figure 2 shows the generation of a residual signal,

10

figure 3a shows a 20 ms segment of a voiced speech  
signal,

figure 3b shows the autocorrelation function of a  
residual signal corresponding to the segment of  
figure 3a, and

15

figure 4 shows an example of an autocorrelation  
function where pitch doubling could arise.

20

**DETAILED DESCRIPTION**

Figure 1 shows a block diagram of an example of a  
pitch detector 1 according to the invention. A speech  
signal 2 is sampled with a sampling rate of 8 kHz in  
the sampling circuit 3 and the samples are divided

25

into segments or frames of 160 consecutive samples. Thus, each segment corresponds to 20 ms of the speech signal.

5 This is the sampling and segmentation normally used for the speech processing in a standard mobile telephone.

10 Each segment of 160 samples is then processed in a filter 4, which will be described in further detail below.

15 First, however, the nature of speech signals will be discussed briefly. In a classical approach a speech signal is modelled as an output of a slowly time-varying linear filter. The filter is either excited by a quasi-periodic sequence of pulses or random noise depending on whether a voiced or an unvoiced sound is to be created. It is important to note the definition of "voiced sound" in the context of this invention. The pulse train which creates "voiced sounds" as used herein, is produced by pressing air out of the lungs through the vibrating vocal cords. The period of time between the pulses is called the pitch period and is of great importance for the singularity of the speech. On the other hand,

20

25

unvoiced sounds are generated by forming a constriction in the vocal tract and produce turbulence by forcing air through the constriction at a high velocity. This description deals with the detection of the pitch period of voiced sounds, and thus unvoiced sounds will not be further considered.

As speech is a varying signal also, the filter has to be time-varying. However, the properties of a speech signal change relatively slowly with time. It is reasonable to believe that the general properties of speech remain fixed for periods of 10-20 ms. This has led to the basic principle that if short segments of the speech signal are considered, each segment can effectively be modelled as having been generated by exciting a linear time-invariant system during that period of time. The effect of the filter can be seen as caused by the vocal tract, the tongue, the mouth and the lips.

As mentioned, voiced speech can be interpreted as the output signal from a linear filter driven by an excitation signal. This is shown in the upper part of figure 2 in which the pulse train 21 is processed by the filter 22 to produce the voiced speech signal 23. A good signal for the detection of the pitch period

is obtained if the excitation signal can be extracted from the speech. By estimating the filter parameters A in the block 24 and then filtering the speech through an inverse filter 25 based on the estimated filter parameters, a signal 26 similar to the excitation signal can be obtained. This signal is called the residual signal. This process is shown in the lower part of figure 2. The blocks 24 and 25 are included in the filter 4 in figure 1.

The estimation of the filter parameters is based on an all-pole modelling which is performed by means of the method called linear predictive analysis (LPA). The name comes from the fact that the method is equivalent with linear prediction. This method is well known in the art and will not be described in further detail here.

The estimation of the pitch is based on the autocorrelation of the residual signal, which is obtained as described above. Thus, the output signal from the filter 4 is taken to an autocorrelation calculation unit 5. Figure 3a shows an example of a 20 ms segment of a voiced speech signal and figure 3b the corresponding autocorrelation function of the residual signal. It will seen from figure 3a

that the actual pitch period is about 5.25 ms corresponding to 42 samples, and thus the pitch estimation should end up with this value.

5 Thus, the autocorrelation function may be calculated directly of the speech signal instead of the residual signal, or other conformity functions may be used instead of the autocorrelation function. As an example, a cross correlation could be calculated  
10 between the speech signal and the residual signal.

Further, different sampling rates and sizes of the segments may be used.

15 The next step in the estimation of the pitch is to apply a peak picking algorithm to the autocorrelation function provided by the unit 5. This is done in the peak detector 6 which identifies the maximum peak (i.e. the largest value) in the autocorrelation  
20 function. The index value, i.e. the sample number or the lag, of the maximum peak is then used as a preliminary estimate of the pitch period. In the case shown in figure 3b it will be seen that the maximum peak is actually located at a lag of 42 samples. The  
25 search of the maximum peak is only performed in the

range where a pitch period is likely to be located.  
In this case the range is set to 60-333 Hz.

5 However, this basic pitch estimation algorithm is not  
always sufficient. In some cases pitch doubling may  
occur, i.e. due to distortion, the peak in the  
autocorrelation function corresponding to the true  
pitch period is not the highest peak, but instead the  
10 highest peak appears at twice the pitch period. The  
highest peak could also appear at other multiples of  
the actual pitch period (pitch tripling, etc.)  
although this occurs relatively rarely. A typical  
example where pitch doubling would arise is shown in  
figure 4, which again shows the autocorrelation  
15 function of the residual signal. Here, too, the  
correct pitch period would be 42 around samples, but  
the peak at twice the pitch period, i.e. around 84  
samples, is actually higher than the one at 42  
samples. The basic pitch estimation algorithm would  
20 therefore estimate the pitch period to 84 samples and  
pitch doubling would thus occur.

25 To avoid the problem of pitch doubling, the pitch  
detection algorithm is therefore improved as  
described below.

After the preliminary pitch estimate has been determined, it is checked in the risk check unit 7 whether there is any risk of pitch doubling. All peaks with a peak value higher than 75% of the maximum peak are detected and the further processing depends on the result of this detection. If only one peak is detected, i.e. the original maximum peak, there is no need to perform a process to avoid pitch doubling. In this situation the preliminary pitch estimate is used as the final pitch estimate. If, however, more than one peak is detected, there is a risk of pitch doubling and a further algorithm must be performed to ensure that the correct peak is selected as the pitch estimate. This is performed in the unit 8.

To identify the peak corresponding to the actual pitch period a modified signal is provided based on the location of the peaks in the autocorrelation of the residual signal. This modified signal, referred to as binary signal, consists of only ones and zeros. The binary signal is set to one where the high peaks are found in the autocorrelation sequence. All other values are set to zero, and then the autocorrelation of the binary signal is calculated. Since there are only values in some positions in the binary signal,



the resulting autocorrelation will only have a few values separated from zero, and these values will occur around the pitch period of the signal. The pitch period is estimated by observing the distance between the indexes of the values around zero and those separated from zero. If the group of values separated from zero contains only a single value, it is selected as the estimate of the pitch period. If there is more than one value in the group, the one with the highest amplitude in the autocorrelation of the residual signal is chosen.

Sometimes cases may arise where the peak at lag zero is the only peak present. This situation will occur when a peak has been split on two samples and there are no other high peaks in the autocorrelation of the residual signal. In this case the preliminary pitch estimate is chosen as the final pitch estimate.

This algorithm is very simple, and therefore it is well suited in e.g. mobile telephones in which the computational resources are severely limited, and a demand for a low-complexity algorithm is thus placed upon the system. The algorithm may also be implemented in an integrated circuit which may then be used in other types of equipment.

**EQUIVALENTS**

5 Although preferred embodiments of the method and  
apparatus of the present invention have been  
illustrated in the accompanying drawings and  
described in the foregoing description, it will be  
understood that the invention is not limited to the  
embodiments disclosed, but is capable of numerous  
rearrangements, modifications, equivalents and  
10 substitutions without departing from the scope of the  
invention as set forth in the appended claims.

105040" 6229860